PCT

(51) International Patent Classification 6 : H04H 1/00, H04L 1/02, 27/26, H04B 7/12	A1	(11) International Publication Number: WO 99/20007
		(43) International Publication Date: 22 April 1999 (22.04.99)

(54) Title: A SYSTEM AND METHOD FOR MITIGATING INTERMITTENT INTERRUPTIONS IN AN AUDIO RADIO BROADCAST SYSTEM

(57) Abstract

A system (100) for mitigating intermittent interruptions in an audio radio broadcast system is provided wherein a primary radio signal and a redundant radio signal are transmitted from a transmitter subsystem (120) and received by a receiver subsystem (140). The output (112) of an audio source (110) is coupled to a modulator (160) for modulating a radio frequency signal (162) for coupling to a transmit antenna (172). A second output (114) of audio source (110) is coupled to a delay circuit (116), for adding a predetermined time delay thereto. The delayed audio source signal is coupled to a modulator (164) for modulating a second radio frequency signal (166) that is also coupled to the transmit antenna (172). The receiver subsystem (140) receives both the primary radio signal and the delayed redundant radio signal and couples each to a respective demodulator (180, 182). At least demodulator (180) includes a circuit (181) for determining the degradation in the primary radio signal and provides a quality measurement output signal (186) to a blend control circuit (190). The recovered primary audio signal from demodulator (180) is coupled to a second delay circuit (184), the time delay of second delay circuit (184) being substantially equal to the time delay of delay circuit (116). The audio output from delay circuit (184) and the redundant audio output from demodulator (182) are coupled to a blending subsystem (135), wherein each is combined with a weighting factor and then combined together to form a composite audio signal for coupling to the audio output circuit (150).

A SYSTEM AND METHOD FOR MITIGATING INTERMITTENT INTERRUPTIONS IN AN AUDIO RADIO BROADCAST SYSTEM

BACKGROUND OF THE INVENTION
FIELD OF INVENTION

This invention directs itself to a system and method of mitigating the effects of signal fades, temporary blockages or severe channel impairments in an audio broadcasting system. More particularly, the system and method employs the transmission of a primary broadcast signal along with a redundant signal, the redundant signal being delayed by a

5   predetermined amount of time, on the order of several seconds, with respect to the primary broadcast signal. A corresponding delay is incorporated in the receiver for delaying the received primary broadcast signal. Still further, this invention in directed to the concept of detecting degradation in the primary broadcast channel that represents a fade or blockage in the RF signal, before such is perceived by the listener. In response to such detection, the

10 delayed redundant signal is temporarily substituted for the corrupted primary audio signal, acting as a "gap filler" when the primary signal is corrupted or unavailable. More in particular, this invention directs itself to use of a blend function for smoothly transitioning from the primary audio signal to the delayed redundant signal.

PRIOR ART

15 In fixed receiver installations, such as home receivers, the fading statistics are generally stationary, except for occasional temporary fades caused by passing vehicles or aircraft, and so effective mitigation of fades and blockages for these applications can be as simple as installing a better antenna or repositioning the existing antenna. In automotive applications, however, fading and blockage statistics are not stationary, being dependent on

20 the vehicle location and velocity, and effective mitigation requires more sophisticated

SUBSTITUTE SHEET (RULE 26)

- 2 -

methods.

Digital Audio Broadcasting (DAB) techniques are being proposed to improve the quality of broadcasting over conventional AM and FM analog signals. In-Band-On-Channel (IBOC) DAB is a digital broadcasting scheme, likely to be adopted in the United States, in which analog AM or FM signals are simulcast along with the DAB signal. The digital audio signal is generally compressed such that a minimum data rate is required to convey the audio information with sufficiently high fidelity. Terrestrial DAB systems generally have the characteristic that fades and blockages have a more deleterious effect on received audio than they do on analog modulated systems, such as commercial AM or FM broadcast because these DAB systems do not degrade gracefully. This effect is exacerbated for in-band on-channel (IBOC) systems which are constrained to have orders of magnitude lower transmit power than the analog broadcast signals whose frequency band they share. IBOC DAB systems transmit both the analog and DAB signal simultaneously within the required spectral mask of the analog signal alone. Therefore, the IBOC DAB concept allows a station to offer digital audio while retaining its analog listeners, but the digital broadcast will not gain acceptance unless the audio loss due to temporary fades and blockages is mitigated.

SUMMARY OF THE INVENTION

A system for mitigating intermittent interruptions in an audio radio broadcast system is provided. The system includes a source of an audio signal and a transmitter subsystem having a first input coupled to the audio source for modulating at least one first carrier signal with the audio signal to broadcast a primary radio signal. The system also includes a first delay circuit having an input coupled to the audio source for adding a first predetermined time delay to the audio signal to form a delayed redundant audio signal at an output thereof, the output being coupled to a second input of the transmitter subsystem for modulating at least one second carrier signal with the delayed redundant audio signal to broadcast a delayed redundant radio signal simultaneously with the primary radio signal. The system further includes a receiver subsystem for receiving the primary radio signal and the delayed redundant radio signal, the receiver subsystem demodulating the primary radio signal to provide the audio signal to a first output thereof and demodulating the delayed redundant

radio signal to provide the delayed redundant audio signal to a second output thereof. The receiver subsystem includes a circuit for detecting degradation of the received primary radio signal, the circuit for degradation detection providing a quality measurement signal to a third output of the receiver subsystem. The system includes a second delay circuit having an input coupled to this first output of the receiver subsystem for adding a second predetermined time delay to the audio signal to form a delayed primary audio signal at an output thereof, the second predetermined time delay being substantially equal to the first predetermined time delay. Still further, the system includes a blending circuit having a first input coupled to an output of the second delay circuit, and second and third inputs respectively coupled to the second and third outputs of the receiver subsystem for combining a first weighting factor with the delayed primary audio signal and a second weighting factor with the delayed redundant audio signal and combining the weighted delayed primary audio signal with the weighted delayed redundant audio signal to form a composite audio signal. The first weighting factor is smoothly transitioned between a first value and a second value responsive to the quality measurement signal being less than a predetermined threshold value. The second weighting factor is smoothly transitioned between the second value and the first value responsive to the quality measurement signal being less than the predetermined threshold value. Additionally, the system includes an audio output circuit coupled to the blending circuit for converting the composite audio signal to an aural signal.

From another perspective, a method of mitigating intermittent interruptions in an in-band on-channel digital audio broadcast system is provided. Each channel includes at least one carrier signal modulated with an analog audio signal and a plurality of subcarriers modulated with a digital representation of the analog signal, wherein the method comprises the steps of:

(a)   adding a predetermined first time delay to the analog audio signal prior to modulation of the at least one carrier signal, the analog audio signal being delayed relative to the digital representation of the analog audio signal;

(b)   providing a receiver for receiving both the at least one modulated carrier signal and the plurality of modulated subcarriers to recover the delayed analog audio signal and the digital representation of the analog audio signal;

SUBSTITUTE SHEET (RULE 26)

- 4 -

(c)   detecting a predetermined level of degradation in the digital representation of the analog audio signal;

(d)   adding a predetermined second time delay to the digital representation of the analog audio signal and converting the delayed digital representation of the analog audio signal to form a primary audio signal; and,

(e)   substituting the delayed analog audio signal for the primary audio signal when the predetermined level of degradation in detected.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a circuit block diagram of the present invention;

FIGS. 2A-2D are timing diagrams illustrating an aspect of the present invention;

FIG. 3 is a diagram illustrating the spectrum for an in-band on-channel digital audio broadcast system;

FIG. 4 is a circuit block diagram of a portion of the transmitter subsystem for a digital application of the present invention;

FIG. 5 is a circuit block diagram for an alternate configuration of a portion of the transmitter subsystem for a digital application of the present invention;

FIG. 6 is a circuit block diagram of a portion of the receiver subsystem for a digital application of the present invention;

FIG. 7 is a diagram of tie signal spectrum for another application of the present intention;

FIG. 8 is a diagram of the signal spectrum for a non-band on-channel digital audio broadcast system; and

FIG. 9 is a diagram of the spectrum for a purely analog application of the present invention.

DESCRIPTION OF THE PREFERRED EMBODIMENT

Referring to FIGS. 1-9, and particularly to FIG. 1, there is shown system 100 for mitigating intermittent interruptions in an audio radio broadcast system. Conventionally, FM radios mitigate the effects of fades or partial blockages by transitioning from full stereophonic audio to monophonic audio. Some degree of mitigation is achieved because the

- 5 -

stereo information which is modulated on a subcarrier, requires a higher signal-to-noise ratio to demodulate to a given quality level than does the monophonic information which is at the base band. However, there are some blockages which sufficiently "take out" the base band and thereby produce a gap in the reception of the audio signal. System 100 is designed to
5   mitigate even those latter type outages in conventional analog broadcast systems and particularly adapted for use in digital audio broadcast (DAB) systems, where such outages are of an intermittent variety and do not last for more than a few seconds. To accomplish that mitigation, a second signal is simulcasted along with the primary radio signal, the second signal having a redundant audio content.

10   Of particular importance, is the addition of a significant delay in the second signal with respect to the primary broadcast signal. That delay is significantly greater than the processing delays introduced by the digital processing in a DAB system, the delay being greater than 2.0 seconds, and preferably within a 3.0 - 5.0 second range.

              Therefore, in system 100 an audio source 110 provides an output to a
15   transmitter subsystem 120 through coupling line 112. Transmitter subsystem 120 includes a modulator 160 which receives the audio source signal and modulates a carrier signal 162 provided thereto for providing a modulated primary broadcast signal on line 163 for coupling to the output amplifier 170 through an adder 168. Carrier signal 162 may be a radio frequency signal in either the AM or FM frequency band. Audio source 110 also provides an
20   output 114 to a delay circuit 116, delay circuit 116 providing at least a two second delay to the audio signal. The output of delay 116 is coupled to a modulator 164 of the transmitter subsystem 120 for modulating a second carrier signal 166 coupled thereto. The second carrier signal 166 may be a subcarrier within a predetermined broadcast signal spectrum. As the audio signal supplied to modulator 164 is identical to that provided to modulator 160,
25   only delayed with respect to that signal, the modulated output of modulator 164 provides a delayed redundant signal that is coupled to adder 168 by coupling line 165. The combined outputs of modulators 160 and 165 are then coupled to the output amplifier 170 of the transmitter subsystem 120 for coupling to the broadcast antenna 172.

              A receiver subsystem 140 includes an antenna 142 for receiving the signal
30   broadcast from the transmitter antenna 172. The signal received by antenna 142 is coupled to

SUBSTITUTE SHEET (RULE 26)

- 6 -

the front end amplifier/tuning circuits 144 of the receiver subsystem 140. The modulated primary audio broadcast signal is coupled to the primary demodulator 180 by coupling line 146, whereas the modulated delayed redundant audio broadcast signal is coupled to the second demodulator 182 by the coupling line 148. Primary demodulator 180 recovers the audio source signal, as is conventional, and couples the recovered signal to the delay circuit 184. Delay circuit 184 adds a predetermined delay to the recovered primary audio signal for coupling to the output circuitry 150. The delay introduced by the delay circuit 184 is substantially equal to the delay provided by delay circuit 116. Delay circuit 184 is intended to realign the temporal relationship between the primary audio signal and the redundant audio signal, and therefore may introduce a delay time which is slightly greater or slightly less than that introduced by the delay circuit 116, depending upon what other processing delays may have been introduced into one or the other of the two parallel communication paths.

The delay introduced by delay circuits 116, 184 must be sufficiently long so that outages of the parallel broadcast paths are substantially independent, the probability of an outage after such diversity being the square of the probability of an outage without that diversity. The delay time can be quantified with knowledge of the auto-correlation function of the channel outage due to severe impairment. This autocorrelation function is expressed as:

$$R(\tau) = E\{x(t) \bullet x(t-\tau)\} \qquad (1)$$

where: x(t) is defined as the stochastic process of the channel loss probability such that a "1" is assigned when the channel is lost and a "0" is assigned when the channel is clear, and τ is the diversity delay time offset between the two signals. The probability of outage without diversity is expressed as:

$$p = E\{x(t)\} \qquad (2)$$

The autocorrelation function represents the probability of channel outage after diversity improvement as a function of time offset. From a practical point, the diversity delay time offset must be also sufficiently large to allow detection of impairment of the primary signal and the transition from the primary signal to the redundant signal. However, the diversity delay time offset cannot be so great as to impair the listener's stability to quickly

tune the receiver subsystem to a desired channel.

Under non-interference conditions, the recovered primary audio signal is delayed in delay circuit 184 and then coupled to the audio output circuit 150 through blend circuit subsystem 135. Blend circuit subsystem 135 provides the appropriate weighting for

5   combination with the primary audio signal, and the redundant audio signal. The primary audio signal is coupled from delay circuit 184 to a multiplier 194 for weighting supplied from blend control 190 through the coupling line 192. From multiplier 194, the weighted and delayed primary audio signal is coupled to the adder 200 for combination with the weighted redundant audio signal, which during periods of non-interference has a value equal to 0.

10   From adder 200, the signal is coupled to the output amplifier 152 of the output circuit 150. Output amplifier 152 drives the speakers 154 and 156. As will be described in following paragraphs, the primary audio signal may in fact be a stereo audio signal which is transmitted digitally or by conventional FM multiplex broadcast means. Under such circumstances, both audio channels, left and right, are delayed by circuit 184, weighted by circuit 194, and

15   combined with the appropriately weighted redundant signal in adder 200. From adder 200, the two channels would be amplified and coupled to the appropriate speakers in output circuit 150, as represented by speakers 154 and 156.

The circuitry of demodulator 180 includes circuitry 181 for detecting degradation in the received primary radio signal. In other words, the circuitry of demodulator

20   180 includes circuits for making a quality measurement of the recovered primary audio signal, which measurement includes the determination of one or more parameters such as the signal-to-noise ratio, signal power level, and for digital signals the bit error rate and results of a cyclic redundancy check. The quality measurement circuitry 181 provides an output signal on line 186 to the blend control circuit block 190, the output being below a predetermined

25   value when a fade or blockage is detected. Optionally, the demodulator circuit 182 may also be provided with degradation detection circuitry 183 for monitoring the quality of the recovered redundant audio signal, providing a quality measurement signal output on line 188 to blend control circuit block 190. Blend control circuit block 190 outputs a weighting factor on line 192 for controlling the substitution of the recovered, delayed redundant audio signal

30   for the delayed recovered primary audio signal. The weighting factor output from the blend

SUBSTITUTE SHEET (RULE 26)

- 8 -

control circuit block 190 is coupled to an adder 196, wherein the weighting factor is subtracted from unity to provide the proper weighting value to be combined with the recovered delayed redundant audio signal supplied from the demodulator circuitry 182. Thus, when there is no interference detected, the blend control circuit block 190 outputs a weighting

5   factor of unity, which provides a "0" output from adder 196 for combination with the recovered delayed redundant audio signal in the multiplier 198. As the weighting factor is "0", there will be no redundant signal mixed with the primary audio signal in adder 200.

When the quality measurement signal supplied on line 186 indicates detection of sufficient degradation, the quality of the signal being below a predetermined threshold

10   value, blend control circuit block 190 changes the weighting function from a value of "1" to a value of "0", that transition occurring smoothly and over a predetermined time period. That predetermined time period may be within the approximating range of 0.25 - 1.5 seconds. Thus, during the transition the primary audio signal is faded out and the redundant signal faded in, with the delayed redundant audio signal totally replacing the delayed primary audio

15   signal for the remaining period of the outage, and then, responsive to the quality measurement signal on line 186, blend control circuit block 190 transitions the weighting factor from "0" to "1". The transition from "1" to "0" and "0" to "1" is made smoothly over the same predetermined time period so as to avoid any clicks or other audio artifacts which would be noticeable to the user. A sinusoidal transfer function may be utilized for accomplishing the

20   smooth transition between the maximum and minimum weighting values. As the primary signal is delayed by circuit 184 before coupling to the audio output circuit, the quality measurement circuit 181, in effect, predicts an outage in the primary communications path. Upon detection of such an outage, there are several seconds available in which to blend in the redundant audio signal.

25   Referring now to FIG. 2A, there is shown a timing diagram representing the transmitted primary and redundant audio signals. The primary audio signal 210 and redundant audio signal 220 are shown with respect to time. The redundant audio signal is identical to the primary audio signal, but delayed, as shown by the vertical reference lines 213 and 215, indicating the time delay period 212. As previously discussed, the time delay period

30   212 is a time period that is greater than 2.0 seconds.

SUBSTITUTE SHEET (RULE 26)

Referring now to FIG. 2B, there in shown the primary audio signal 210 and redundant delayed audio signal 220 wherein a time segment 230 thereof in subject to sufficient interference or fading to be considered a blockage. Due to the time diversity delay of the redundant audio signal 220 with respect to the primary audio signal 210, the portion of the primary signal 210 within the blockage time period 230 corresponds to the audio segment 240 of the redundant audio signal 220. When the primary audio signal 210 is processed, as shown in FIG. 2C, the blocked signal time segment 230 would be heard by the user subsequent to the time delay established by the delay circuit 184, as previously discussed. However, as the blending circuit 135 responds to the detection of the blockage, the time segment 240 of the redundant audio signal 220 is blended in with the primary audio signal to provide a composite audio signal 225, wherein the audio signal is formed by the primary audio signal 210, except during the time segment 240, wherein the redundant audio signal 220 is substituted therefor.

One application for system 100 is in IBOC DAB, wherein the in-band digital audio broadcast in modulated on 95 orthogonal frequency division modulated subcarriers located on each side of an FM modulated carriers, an shown in FIG. 3. FIG. 3 represents the power spectral densities of the FM modulated broadcast signal 241 and the IBOC DAB signals 242 and 244. The 95 subcarriers of the digital audio broadcast operate the spectrum from 130 kHz - 199 kHz away from the FM center frequency, in both the upper and lower side bands. For digital audio transmission, the block diagram of FIG. 1 is modified to provide digital encoding and decoding as shown in FIGS. 4 and 6.

As shown in FIG. 4, the audio source 110 provides an audio signal on line 114 which is coupled to the delay circuit 116 and from there to modulator 164, as previously described. In this version of the digital audio broadcast system, the redundant audio signal is the FM modulated signal which is being delayed for use in the digital audio receivers to replace corrupter digital data, when necessary. The primary audio signal, provided on line 112, is coupled to a digital encoder 122. The particular digital encoding and compression techniques utilized are not important to the inventive concepts, as herein disclosed, and may represent conventional digital transmission techniques, such as interleaving, convolutional coding and forward error correction techniques. The digitally encoded signal output on line

SUBSTITUTE SHEET (RULE 26)

124 is coupled to the modulator 160, wherein a predetermined number of bits are modulated onto each of the plurality of subcarriers.

At the receiver end, the received redundant radio signal, which is the delayed conventional FM multiplex stereo broadcast signal, is handled as previously described. As shown in FIG. 6, the primary audio signal is coupled to demodulator 180 and from there to delay circuit 184, and then coupled to digital decoder 185. Digital decoder 185 may include a de-interleaver, as well as a forward error correction decoder. Subsequent to decoding, which may include the error correction and detection within the digital decoder block 185, the signal is converted to an analog audio signal in digital-to-analog converter 187. From there, the signal is handled as has previously been described.

Because it is important that the respective time delays of the primary audio signal path and the redundant audio signal path be made equivalent prior to their respective coupling to the blending circuit subsystem 135, and the digital processing circuits of the IBOC DAB system introduces certain delays, it may be desirable to separately account for those relays in the redundant signal path. As shown in FIG. 5, this audio signal from audio source 110 is coupled to the digital encoder 122 by coupling line 112, and from there is coupled to the modulator 160 by coupling line 124, as previously described. However, as opposed to coupling the analog audio signal directly to the modulator 164, through the delay 116, the circuit of FIG. 5 couples the digitized audio signal to a digital decoder 126, by coupling line 125. Digital decoder 126 incorporates the same decoding functions as decoder 185 utilized for the primary audio signal, and includes the digital-to-analog conversion function represented by the block 187 in FIG. 6. Thus, the redundant audio signal is exposed to the same processing delays as the primary audio signal, which delays then need not be accounted for in either of delay circuits 116 or 184. Where such processing delays are invariant, then such may be accounted for by reducing the delay added by the delay circuit 184, to then bring the primary audio signal in temporal alignment with the redundant audio signal.

Another scheme for providing a redundant audio source is represented by the signal spectrum shown in FIG. 7. For a particular FM channel, the signal spectra 246 and 248 represent the respective signal spectrum for each of the FM stereo left + right (L + R) and left

- 11 -

- right (L - R) signals. Displaced from that spectrum is the signal spectrum of the subsidiary communications authorization (SCA) signal, where such subcarrier is modulated with the DAB signals, as the primary radio signal. The SCA signal spectrum is spaced 53 kHz from the FM center frequency. Like the IBOC DAB system, the analog stereo broadcast may be

5   used to form the redundant audio information that is transmitted after a predetermined delay, to form the delayed redundant audio signal.

The time diversity scheme outlined above may also be applied to a non-IBOC DAB system. In a digital-only system, wherein the digital broadcast spectrum is separate and distinct from the conventional analog FM broadcast stations, as shown in FIG. 8, a high data

10   rate primary DAB signal spectrum 254 is provided with a separate redundant, but lower data rate, signal spectrum 256 displaced therefrom. The redundant DAB signal is time delayed with respect to the primary DAB signal, just as in the IBOC system wherein the analog FM is time delayed with respect to the digital signal. Here, the digital redundant signal is time delayed with respect to the primary digital signal. Both signals experience processing delays

15   for encoding, interleaving, de-interleaving, forward error correction decoding and digital-to-analog conversion, for example. Additionally, a delay in the range of 2.0 to 5.0 seconds is added in order to provide a sufficient time diversity to provide the desired uncorrelation between the two parallel transmission paths. As the redundant digital audio signal is only utilized periodically, and for short durations, an economical tradeoff can be made between

20   fidelity and data rate. Therefore, while the listener may detect a temporary degradation in audio quality during the redundant blend duration, the user will not ,experience an outage or any undesirable acoustic artifacts during the transition between the primary and redundant data signals.

As yet another application for the time diversity scheme, as outlined herein, is

25   improving the resistance to outages for conventional FM broadcasts. In such a scheme, the broadcast spectrum, as shown in FIG. 9, provides for the conventional stereo signal spectra 246, 248 as well as an SCA signal spectrum 250 which in this invention carries a redundant audio signal. In this scheme, the FM stereo broadcast is the primary audio signal and is transmitted undelayed, while the redundant information that is modulated on an SCA

30   subcarrier would be delayed by a time period within the range of approximately 2.0 to 5.0

SUBSTITUTE SHEET (RULE 26)

seconds.

Irrespective of whether the primary audio signal is broadcast as an analog or digital signal, the key to mitigating outages is the broadcast of a redundant signal which is delayed with respect to the primary signal by a sufficient time period so that the two

5   transmission channels are statistically uncorrelated with respect to a fade or outage. One limitation on the delay time period is the effect that such would have on tuning from one station to another. In addition to constraining the delay time, that limitation can be overcome by substituting the redundant signal during the tuning intervals. Also important is the scheme by which the redundant audio signal is substituted for the primary signal during the

10   mitigation process. As previously discussed, system 100 provides for a smooth transition wherein the redundant signal is blended in to the input to the audio output circuit while the "soon to be degraded" primary signal in blended out. As the primary audio signal is delayed for a time period greater than 2.0 seconds, system 100 detects a fade or blockage of the primary signal long before a listener would detect it, providing time for a smooth and

15   relatively slow transition to the redundant signal. As such substitutions are intermittent, and for brief periods of time, the quality of the redundant signal need not be at the same level as that of the primary signal. In this case of an IBOC DAB system, the redundant signal may be the lower quality conventional FM broadcast signal, or a lower data rate digital signal, modulated on one or more SCA subcarriers or other specially assigned subcarriers. In the

20   case of a conventional analog FM broadcast signal, such may be backed up with a redundant analog signal modulated on an SCA subcarrier. Although the above discussion has centered around broadcast in the FM signal spectra, the time diversity and blending functions are equally applicable to transmissions in the AM band, and in particular to digital audio broadcast in the AM band, wherein a conventional analog AM broadcast may be utilized as

25   the redundant audio signal for a digital broadcast of the same audio material.

In carrying out the method of mitigating intermittent interruptions in an audio radio broadcast, the following steps are carried out.

An audio signal is provided and used to modulate at least one radio frequency signal. Where the broadcast is intended to be a digital radio broadcast, the modulation step

30   would include the step of digitally encoding the audio signal. Whether digital or audio, such

SUBSTITUTE SHEET (RULE 26)

signal would be considered the primary audio signal.

A first time delay is also added to the audio signal to form a delayed redundant audio signal. The delayed redundant audio signal may be an analog or a digital signal, and if a digital signal is utilized such may be at a lower data rate than that of the primary signal. A

5   second radio frequency signal, which may be a subcarrier of the first radio frequency signal, is modulated with the delayed redundant audio signal. The modulated primary audio signal and the modulated redundant audio signal are received and the respective audio signals recovered therefrom.

A quality measurement is made of at least a radio signal carrying the primary

10   audio signal information. The quality measurement may include a measure of such parameters as signal-to-noise ratio, bit error rate, signal power level and results of a cyclic redundancy check.

A second predetermined time delay is added to the recovered primary audio signal to form a delayed primary audio signal, the second predetermined time delay being

15   substantially equal to that of the first predetermined time delay in order to temporally align the primary audio signal with the delayed redundant audio signal. The time delay is selected from a time period within the approximating range of 2.0 to 5.0 seconds.

A first weighting factor is established, the first weighting factor being equal to 1.0 when the quality measurement is at least as great as a predetermined threshold value and

20   smoothly transitions to 0.0 over a predetermined time period when, the quality measurement is less than the predetermined threshold value, indicating a fade or blockage of the signal.

A second weighting factor is established, the second weighting factor being equal 0.0 when the quality measurement is at least as great as the predetermined threshold value and smoothly transitioning to 1.0 over the predetermined time period when the quality

25   measurement is less than the predetermined threshold value. The first weighting factor and the delayed primary audio signal are combined, and the second weighting factor is combined with the delayed redundant audio signal.

The weighted delayed primary audio signal is combined with the weighted delayed redundant audio signal to form a composite audio signal.

30   Lastly, the composite audio signal is coupled to an audio output circuit.

SUBSTITUTE SHEET (RULE 26)

- 14 -

In particular, the above described method may be employed with a digital audio broadcast in that the audio source signal is first digitally encoded before being utilized to modulate a radio frequency signal. That radio frequency signal may include one or more subcarriers which are spaced from a center frequency of an FM broadcast signal spectrum

5   within the approximating range of 130 - 199 kilohertz. A second radio frequency signal may comprise one subcarrier of a conventional analog FM multiplex stereo broadcast signal spectrum, which would then be delayed as previously discussed. Alternately, the redundant audio information may be modulated on an SCA subcarrier of an FM broadcast signal spectrum, or alternately, the primary digital audio signal may be modulated on one or more

10   radio frequency signals within the SCA signal spectra as the redundant signal for either a primary digital audio broadcast or a conventional analog FM audio broadcast.

Although this invention has been described in connection with specific forms and embodiments thereof, it will be appreciated that various modifications other than those discussed above may be resorted to without departing from the spirit or scope of the invention, for example, equivalent elements may be substituted for those specifically shown and described, certain features may be used independently of other features, and in certain cases, particular locations of elements may be reversed or interposed, all without departing from the spirit or scope of the invention as defined in the appended claims.

SUBSTITUTE SHEET (RULE 26)

WHAT IS CLAIMED IS:

1. A system for mitigating intermittent interruptions in an audio radio broadcast system, comprising:

a source of an audio signal;

transmitter means having a first input coupled to said audio source for
5   modulating at least one first carrier signal with said audio signal to broadcast a primary radio signal;

first delay means having an input coupled to said audio source for adding a first predetermined time delay to said audio signal to form a delayed redundant audio signal at an output thereof, said output being coupled to a second input of said transmitter means for
10   modulating at least one second carrier signal with said delayed redundant radio signal to broadcast a delayed redundant radio signal simultaneously with said primary radio signal;

receiver means for receiving said primary radio signal and said delayed redundant radio signal, said receiver means demodulating said primary radio signal to provide said audio signal to a first output thereof and demodulating said delayed redundant radio
15   signal to provide said delayed redundant audio signal to a second output thereof, said receiver means including means for detecting degradation of said received primary radio signal, said means for degradation detection providing a quality measurement signal to a third output of said receiver means;

second delay means having an input coupled to said first output of said
20   receiver means for adding a second predetermined time delay to said audio signal to form a delayed primary audio signal at an output thereof, said second predetermined time delay being substantially equal to said first predetermined time delay;

blending means having a first input coupled to an output of said second delay means and second and third inputs respectively coupled to said second and third outputs

of said receiver means for combining a first weighting factor with said delayed primary audio signal and a second weighting factor with said delayed redundant audio signal and combining said weighted delayed primary audio signal with said weighted delayed redundant audio signal to form a composite audio signal, said first weighting factor being smoothly transitioned between a first value and a second value responsive to said quality measurement signal being less than a predetermined threshold value, said second weighting factor being smoothly transitioned between said second value and said first value responsive to said quality measurement signal being less than said predetermined threshold value; and

audio output means coupled to said blending means for converting said composite audio signal to an aural signal.

2.   The system as recited in Claim 1 where said first predetermined time delay is equal to or greater than 2.0 seconds.

3.   The system as recited in Claim 1 further including digital encoding means having an input coupled to said audio source and an output coupled to said first input of said transmitter means.

4.   The system as recited in Claim 3 further including digital decoder means having an input coupled to said output of said second delay means and an output coupled to said first input of said blending means.

5.   The system as recited in Claim 4 where said means for detecting degradation of said received primary radio signal. includes means for determining one or more parameters selected from the group consisting of signal-to-noise ratio, bit error rate, signal power level and cyclic redundancy check.

6.   The system as recited in Claim 4 where said second carrier is at least one FM stereo multiplex subcarrier within an FM broadcast signal spectrum.

7.   The system as recited in Claim 6 where said first carrier is at least one subcarrier spaced at least 53 kilohertz from a center frequency of said FM broadcast signal spectrum.

8.   The system as recited in Claim 6 where said first carrier is at least one SCA subcarrier of said FM broadcast signal spectrum.

9.   The system as recited in Claim 1 where said second carrier is at least one

SUBSTITUTE SHEET (RULE 26)

radio frequency signal within an FM broadcast signal spectrum.

10. The system as recited in Claim 9 where said first carrier is at least one SCA subcarrier of said FM broadcast signal spectrum.

11. The system as recited in Claim 1 where said first weighting factor is a function smoothly transitioning between 1.0 and 0.0 responsive to said quality measurement signal being less than said predetermined threshold value, said second weighting factor being a function smoothly transitioning between 0.0 and 1.0 responsive to said quality measurement signal being less than said predetermined threshold value.

12. A method of mitigating intermittent interruptions in an audio radio broadcast, comprising the steps of:

(a)   providing an audio signal;

(b)   modulating at least one first radio frequency signal with said audio signal for transmitting said audio signal as a first radio signal;

(c)   adding a first predetermined time delay to said audio signal to form a delayed redundant audio signal;

(d)   modulating at least one second radio frequency signal with said delayed redundant audio signal for transmitting said delayed redundant audio signal as a second radio signal;

(e)   receiving said first and second radio signals and recovering said audio signal and said delayed redundant audio signal;

(f)   making a quality measurement of at least said received first radio signal;

(g)   adding a second predetermined time delay to said recovered audio signal to form a delayed primary audio signal, said second predetermined time delay being substantially equal to said first predetermined time delay;

(h)   establishing a first weighting factor, said first weighting factor being equal to 1.0 when said quality measurement is at least as great as a predetermined threshold value and smoothly transitioning to 0.0 over a predetermined time period when said quality measurement is less than said predetermined threshold value;

(i)   establishing a second weighting factor, said first weighting

factor being equal to 0.0 when said quality measurement is at least as great as said predetermined threshold value and smoothly transitioning to 1.0 over said predetermined time period when said quality measurement is less than said predetermined threshold value;

(j) combining said first weighting factor and said delayed primary audio signal, and combining said second weighting factor and said delayed redundant audio signal;

(k) combining said weighted delayed primary audio signal and said weighted delayed redundant audio signal to form a composite audio signal; and

(l) providing an audio output circuit and coupling said composite audio signal thereto.

13. The method as recited in Claim 12 where said step of modulating at least one first radio frequency signal includes the step of digitally encoding said audio signal.

14. The method as recited in Claim 13 where said step of receiving includes the step of decoding said recovered audio signal.

15. The method as recited in Claim 12 where said step of adding a first predetermined time delay includes the step of selecting a time delay within the approximating range of 2.0 - 5.0 seconds.

16. The method as recited in Claim 14 where the step of modulating at least one first radio frequency signal includes the step of modulating at least one carrier spaced within the approximating range of 130 - 199 kilohertz from a center frequency of an FM broadcast signal spectrum with said digitally encoded audio signal.

17. The method as recited in Claim 16 where the step of modulating at least one second radio frequency signal includes the step of modulating at least one radio frequency signal within an FM broadcast signal spectrum with said delayed redundant audio signal.

18. The method as recited in Claim 16 where the step of modulating at least one second radio frequency signal includes the step of modulating at least one SCA subcarrier of said FM broadcast signal spectrum with said delayed redundant audio signal.

19. The method as recited in Claim 12 where said step of making a quality measurement includes the step of determining one or more parameters selected from the

group consisting of signal-to-noise ratio, bit error rate, signal power level and cyclic redundancy check.

20.   A method of mitigating intermittent interruptions in an in-band on-channel digital audio broadcast system, wherein each channel includes at least one carrier signal modulated with an analog audio signal and a plurality of subcarriers modulated with a digital representation of the analog audio signal, comprising the steps of:

(a)   adding a predetermined first time delay to the analog audio signal prior to modulation of the at least one carrier signal, the analog audio signal being delayed relative to the digital representation of the analog audio signal;

(b)   providing a receiver for receiving both said at least one modulated carrier signal and said modulated subcarriers to recover said delayed analog audio signal and said digital representation of the analog audio signal;

(c)   detecting a predetermined level of degradation in said digital representation of the analog audio signal;

(d)   adding a predetermined second time delay to said digital representation of the analog audio signal and converting said delayed digital representation of the analog audio signal to form a primary audio signal; and

(e)   substituting said delayed analog audio signal for said primary audio signal when said predetermined level of degradation is detected.

21.   A method of in-band on-channel broadcasting comprising the steps of:

providing a first signal to be broadcast;

providing a second signal to be broadcast;

delaying one of said first signal and said second signal with respect to the other of said first signal and said second signal;

modulating a first carrier with a first one of said first signal and said second signal;

orthogonal frequency division modulating a plurality of subcarriers with a second one of said first signal and said second signal, said plurality of subcarriers being positioned in upper and lower sidebands with respect to said first carrier;

- 20 -

combining said first carrier and said plurality of subcarriers to produce a composite signal; and

transmitting said composite signal.

22.   A method of in-band on-channel broadcasting as recited in claim 21, wherein said first signal comprises an analog signal and said second signal comprises a digital signal.

23.   A method of in-band on-channel broadcasting as recited in claim 21, wherein said first signal comprises a digital signal and said second signal comprises an analog signal.

24.   A method of in-band on-channel broadcasting as recited in claim 21, wherein said first signal and said second signal represent the same audio information.

25.   A method of in-band on-channel broadcasting as recited in claim 21, wherein:

said first carrier is frequency modulated;

said upper sideband ranges from about 130 kHz to about 199 kHz from said first carrier; and

said lower sideband ranges from about -130 kHz to about -199kHz from said first carrier.

26.   A method of in-band on-channel broadcasting as recited in claim 25, each of said upper and lower sidebands contains 95 of said subcarriers.

27.   An in-band on-channel broadcasting transmitter comprising:

means for providing a first signal to be broadcast;

means for providing a second signal to be broadcast;

means for delaying one of said first signal and said second signal with respect to the other of said first signal and said second signal;

means for modulating a first carrier with a first one of said first signal and said second signal;

means for orthogonal frequency division modulating a plurality of subcarriers with a second one of said first signal and said second signal, said plurality of subcarriers being positioned in upper and lower sidebands with respect to said first carrier;

SUBSTITUTE SHEET (RULE 26)

- 21 -

means for combining said first carrier and said plurality of subcarriers to produce a composite signal; and

means for transmitting said composite signal.

28. An in-band on-channel broadcasting transmitter as recited in claim 27, wherein said first signal comprises an analog signal and said second signal comprises a digital signal.

29. An in-band on-channel broadcasting transmitter as recited in claim 27, wherein said first signal comprises a digital signal and said second signal comprises an analog signal.

30. An in-band on-channel broadcasting transmitter as recited in claim 27, wherein said first signal and said second signal represent the same audio information.

31. An in-band on-channel broadcasting transmitter as recited in claim 27, wherein:

said first carrier is frequency modulated;

said upper sideband ranges from about 130 kHz to about 199 kHz from said first carrier; and

said lower sideband ranges from about -130 kHz to about -199kHz from said first carrier.

32. An in-band on-channel broadcasting transmitter as recited in claim 31, each of said upper and lower sidebands contains 95 of said subcarriers.

33. A method of receiving an in-band on-channel broadcast signal including a first carrier modulated by a first signal, a plurality of subcarriers positioned in upper and lower sidebands with respect to said first carrier to be broadcast and orthogonal frequency division modulated by a second signal, wherein one of said first signal and said second signal is delayed with respect to the other of said first signal and said second signal, said method comprising the steps of:

demodulating said first carrier to produce a first demodulated signal;

demodulating said plurality of subcarriers to produce a second demodulated signal;

SUBSTITUTE SHEET (RULE 26)

delaying one of said first and second demodulated signals with respect to the other of said first and second demodulated signals;

selecting one said first and second demodulated signals to be used to produce an output signal; and

5   producing an output signal in response to the selected one of said first and second demodulated signals.

34.   A method of receiving an in-band on-channel broadcast signal as recited in claim 33, wherein said first signal comprises an analog signal and said second signal comprises a digital signal.

10   35.   A method of receiving an in-band on-channel broadcast signal as recited in claim 33, wherein said first signal comprises a digital signal and said second signal comprises an analog signal.

36.   A method of receiving an in-band on-channel broadcast signal as recited in claim 33, wherein said first signal and said second signal represent the same audio

15   information.

37.   A method of receiving an in-band on-channel broadcast signal as recited in claim 33, wherein:

said first carrier is frequency modulated;

said upper sideband ranges from about 130 kHz to about 199 kHz from said

20   first carrier; and

said lower sideband ranges from about -130 kHz to about -199kHz from said first carrier.

38.   A method of receiving an in-band on-channel broadcast signal as recited in claim 37, each of said upper and lower sidebands contains 95 of said subcarriers.

25   39.   A method of receiving an in-band on-channel broadcast signal as recited in claim 33, wherein said step of selecting one said first and second demodulated signals to be used to produce an output signal comprises the step of:

detecting degradation of one said first and second demodulated signals by determining one or more parameters selected from the group consisting of signal-to-noise

30   ratio, bit error rate, signal power level and cyclic redundancy check.

SUBSTITUTE SHEET (RULE 26)

- 23 -

40.   A method of receiving an in-band on-channel broadcast signal as recited in claim 33, wherein said step of selecting one said first and second demodulated signals to be used to produce an output signal comprises the step of:

providing a quality measurement signal representative of said first signal;

5   establishing a first weighting factor when said quality measurement is less than said predetermined threshold value;

establishing a second weighting factor when said quality measurement is less than said predetermined threshold value;

combining said first weighting factor and said first signal, and combining said

10   second weighting factor and said second signal; and

combining said weighted first signal and said weighted second signal to form a composite audio signal; and

coupling said composite audio signal to an output.

41.   A receiver for an in-band on-channel broadcast signal including a first

15   carrier modulated by a first signal, a plurality of subcarriers positioned in upper and lower sidebands with respect to said first carrier to be broadcast and orthogonal frequency division modulated by a second signal, wherein one of said first signal and said second signal is delayed with respect to the other of said first and said second signal, said receiver comprising:

means for demodulating said first carrier to produce a first demodulated

20   signal;

means for demodulating said plurality of subcarriers to produce a second demodulated signal;

means for delaying one of said first and second demodulated signals with respect to the other of said first and second demodulated signals;

25   means for selecting one said first and second demodulated signals to be used to produce an output signal; and

means for producing an output signal in response to the selected one of said first and second demodulated signals.

SUBSTITUTE SHEET (RULE 26)

42.   A receiver for an in-band on-channel broadcast signal as recited in claim 41, wherein said first signal comprises an analog signal and said second signal comprises a digital signal.

43.   A receiver for an in-band on-channel broadcast signal as recited in claim 41, wherein said first signal comprises a digital signal and said second signal comprises an analog signal.

44.   A receiver for an in-band on-channel broadcast signal as recited in claim 41, wherein said first signal and said second signal represent the same audio information.

45.   A receiver for an in-band on-channel broadcast signal as recited in claim 41. wherein:

said first carrier is frequency modulated;

said upper sideband ranges from about 130 kHz to about 199 kHz from said first carrier; and

said lower sideband ranges from about -130 kHz to about -199kHz from said first carrier.

46.   A receiver for an in-band on-channel broadcast signal as recited in claim 45, each of said upper and lower sidebands contains 95 of said subcarriers.

47.   A receiver for an in-band on-channel broadcast signal as recited in claim 41, wherein said means for selecting one said first and second demodulated signals to be used to produce an output signal comprises:

means for detecting degradation of one said first and second demodulated signals by determining one or more parameters selected from the group consisting of signal-to-noise ratio, bit error rate, signal power level and cyclic redundancy check.

48.   A receiver for an in-band on-channel broadcast signal as recited in claim 41, wherein said means for selecting one said first and second demodulated signals to be used to produce an output signal comprises:

means for providing a quality measurement signal representative of said first signal;

SUBSTITUTE SHEET (RULE 26)

means for establishing a first weighting factor when said quality measurement is less than said predetermined threshold value;

means for establishing a second weighting factor when said quality measurement is less than said predetermined threshold value;

5   means for combining said first weighting factor and said first signal, and combining said second weighting factor and said second signal; and

means for combining said weighted first signal and said weighted second signal to form a composite audio signal; and

means for coupling said composite audio signal to an output.

SUBSTITUTE SHEET (RULE 26)

FIG.1

FIG.2A

FIG.2B

FIG.2C

FIG.2D

FIG.3

4/7

FIG.4

FIG.5

FIG.6

FIG.7

FIG.8

FIG.9

INTERNATIONAL SEARCH REPORT

A. CLASSIFICATION OF SUBJECT MATTER

IPC 6   H04H1/00   H04L1/02   H04L27/26   H04B7/12

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 6   H04H   H04L   H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category °	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	EP 0 744 847 A (PHILIPS COMM ENTREPRISE ;PHILIPS ELECTRONICS NV (NL)) 27 November 1996 see abstract	1-5
Y	see figure 1	11-15,19
Y	EP 0 782 275 A (NIPPON ELECTRIC CO) 2 July 1997 see abstract see figure 2	11-15,19
X	EP 0 771 084 A (NIPPON ELECTRIC CO) 2 May 1997 see abstract see page 3, line 19 - line 40	1,2,11, 12,15,19
Y	see figure 1	3-7,9, 10,13, 14,16,17

-/--

| X | Further documents are listed in the continuation of box C. | X | Patent family members are listed in annex. |

° Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search	Date of mailing of the international search report
10 February 1999	25/02/1999

Name and mailing address of the ISA	Authorized officer
European Patent Office, P.B. 5818 Patentlaan 2 NL - 2280 HV Rijswijk Tel. (+31-70) 340-2040, Tx. 31 651 epo nl, Fax: (+31-70) 340-3016	Simon, V

Form PCT/ISA/210 (second sheet) (July 1992)

page 1 of 2

INTERNATIONAL SEARCH REPORT

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication,where appropriate, of the relevant passages	Relevant to claim No.
X	US 3 781 795 A (ZEGERS L) 25 December 1973 see abstract	1,2
Y	see figure 1	3-7,9,10

X	US 3 665 395 A (BOCHMANN KARLHEINZ) 23 May 1972 see abstract see column 4, line 35 - line 75	1,2
Y	see figure 3	3-7,9,10

Y	US 4 382 299 A (DIETERICH CHARLES B) 3 May 1983 see abstract see claims 1,3,4	3-7,9, 10,13, 14,16, 17,20-48
A	see figures 2,4	1,12,15, 19

P,Y	EP 0 825 736 A (LUCENT TECHNOLOGIES INC) 25 February 1998 see abstract see page 5, line 38 - page 6, line 12 see page 9, line 4 - line 20 see figures 3,8	20-48

P,Y	US 5 757 854 A (VIGIL A J ET AL) 26 May 1998 see abstract see column 13, line 4 - line 38 see figure 16	20-48

1

INTERNATIONAL SEARCH REPORT

.nformation on patent family members

Patent document cited in search report		Publication date	Patent family member(s)		Publication date
EP 0744847	A	27-11-1996	CN	1146102 A	26-03-1997
			JP	9036845 A	07-02-1997
			US	5835483 A	10-11-1998
EP 0782275	A	02-07-1997	JP	9186638 A	15-07-1997
EP 0771084	A	02-05-1997	JP	9116475 A	02-05-1997
			US	5859870 A	12-01-1999
US 3781795	A	25-12-1973	NL	7106776 A	21-11-1972
			AU	464117 B	14-08-1975
			AU	4232972 A	22-11-1973
			BE	783545 A	16-11-1972
			CA	956727 A	22-10-1974
			DE	2221171 A	30-11-1972
			DK	136926 B	12-12-1977
			FR	2138107 A	29-12-1972
			GB	1349815 A	10-04-1974
			SE	369976 B	23-09-1974
US 3665395	A	23-05-1972	CH	474923 A	30-06-1969
			GB	1210846 A	04-11-1970
US 4382299	A	03-05-1983	DE	3144216 A	09-06-1982
			FR	2494018 A	14-05-1982
			GB	2087627 A,B	26-05-1982
			JP	57123508 A	02-08-1982
EP 0825736	A	25-02-1998	CA	2208830 A	22-02-1998
			JP	10093516 A	10-04-1998
US 5757854	A	26-05-1998	US	5465396 A	07-11-1995
			EP	0679303 A	02-11-1995
			JP	8505989 T	25-06-1996
			WO	9416506 A	21-07-1994
			US	5850415 A	15-12-1998

Form PCT/ISA/210 (patent family annex) (July 1992)